

THE DOCUMENT COMPANY

XEROX

Xerox Document Centre ColorSeries 50 LP/ST Novell NetWare® Quick Install

Before You Start:

- For all NetWare environments, record the following information, making sure to capture case-sensitive information:
 - a) **Frame Type**
 - b) **Print Server Name**
 - c) assigned **Print Server Password** (optional)
 - d) **NDS Tree** and **NDS Context Name** (for NDS only).
- When using Novell NetWare version 3.x, you must have a Queue and Print Server created for the server, and know the Frame Type being used.
- When using Novell NetWare 4.x or 5.x for a **Bindery** installation, you must create the Queue and Print Server as Bindery objects, and know the context in which they are created. For a **Bindery** installation, you must also record the File Server Name.
- When using Novell NetWare 4.x or 5.x for an **NDS** installation, you must create the Printer, Print Server and Queue, and know the Context and Tree Name in which they are created.
- Decide now if you will use CentreWare Internet Services or CentreWare Printer Admin Services to customize printer connectivity settings.

Step 1 Set Up the Printer

1. Run NWADMIN, NWADMIN32 or PCONSOLE to set up a printer and queue objects. Refer to the Novell documentation, if needed.
2. Press the **Administration** button, located on the printer Control Panel.
3. Press **Tools** on the Touch Screen.
4. Using the keypad, enter your **Access Number** and then press **Enter** on the Touch Screen. The default Access Number is 11111. It may have been changed by a System Administrator.
5. Press **Machine Setup** on the Touch Screen. The list of available Items and their current settings are displayed.
6. Press **IP Address** in the Items list, or use the scroll buttons to locate the **IP Address** field.
7. Press **Change Settings** on the Touch Screen.
8. After entering the IP Address using the keypad, press **Save**.
9. Press **Frame Type**, located in the Items list, or use the scroll buttons to locate the **Frame Type**.
10. Press **Change Settings** on the Touch Screen.
11. After pressing the desired button for **Frame Type**, press **Save**.
12. If you are using Token Ring, also set the **Source Routing** value.
13. Press **Close** repeatedly until you exit the Administration screens.
14. Power off and power on the printer. Allow at least 30 seconds between powering off and powering on the printer. A Configuration Report will print in approximately 5 minutes. The information on the Configuration Report can be very helpful in completing the network installation and troubleshooting problems with your printer.
15. Continue with *Step 2 Customize Printer Connectivity Settings*.

For assistance, contact your local Xerox Customer Support Center: USA: 1-800-821-2797 Canada: 1-800-939-3769

Bustled Controller, Part Numbers 97N00893 and 97N00894 are for use with Xerox Corp. Digital Color Product Model YFA-1.

THE DOCUMENT COMPANY

XEROX

Xerox Document Centre ColorSeries 50 LP/ST Novell NetWare® Quick Install

Step 2 Customize Printer Connectivity Settings

If you use CentreWare Printer Admin Services:

1. Install the Printer Admin Services software.
2. Start the Printer Admin Services program. From a Windows workstation click **Start > Programs > Xerox CentreWare Color > Printer Admin Services**.
3. From the main Printer Admin Services window, click **NetWare** and select the printer that you want to install from the list of printers.
4. Click **OK** and then click **Settings**.
5. Click on the **Network** tab.
6. Review the displayed settings and make any changes, if necessary.
7. Click on the **NetWare** tab and then review and edit the **Print Server Name, Print Server Password, Poll Interval** and **SAP Interval** settings, as needed.
 - a) For a Bindery installation, you must also enter a name in the **File Server 1** field. Enter information in other fields as desired.
 - b) For a NDS installation, you must enter information in the **Tree Name** and **Context** fields.

8. If you are using IP, continue with Step 9. If you are not using IP, skip to Step 11.
9. Click on the **TCP/IP** tab.
10. Review and edit any fields, if necessary. If you enable DHCP, be sure to save the new Configuration Report that will print approximately 5 minutes after you power off and power on the printer, since the IP Address may have changed. You will need the new address the next time you access the settings.
11. When you have finished entering the Settings data, click **Apply, OK** and then **Exit**.
12. Power off and power on the printer. Allow at least 30 seconds between powering off and powering on the printer. A Configuration Report will print in approximately 5 minutes. The information on the Configuration Report can be very helpful in completing the network installation and troubleshooting problems with your printer.
13. Continue with *Step 3 Print a Test Page*.

Step 2 Customize Printer Connectivity Settings

If you use CentreWare Internet Services:

1. At your workstation, open the Internet Explorer or NetScape navigator browser.

2. In the browser, enter the IP Address for the printer and press the **Enter** key. The Internet Services Home Page is displayed.
3. Click on the **Properties** button.
4. Click **Connectivity, Protocols, and NetWare** to view NetWare information.
5. Review and edit the NetWare settings.
6. Click **Apply New Settings** if any changes were made. Provide a **User Name** and **Password** when prompted. The default User Name is **Admin** with a capital "A" and the default password is **11111**.
7. Power off and power on the printer. Allow a full 30 seconds between powering off and powering on the printer.
8. Continue with *Step 3 Print a Test Page*.

Step 3 Print a Test Page

1. Install the network printer driver for your workstation environment, and print a test page. Details on installing printer drivers, printing a test page, and other printing options are provided in the *Xerox Document Centre ColorSeries 50 LP/ST Printer User Guide*.
2. Details on installing the printer with NetWare is in the *Xerox Document Centre ColorSeries 50 LP/ST Printer Installation Guide*.