

***Yellow Printing
XP12 1.1 SPI***

Problems Addressed:

After a large number of prints, the XP12 abruptly starts printing all jobs as a single yellow separation.

Solution:

Download the enclosed 1-7SN1D.ps to the Fiery.

This update consists of the following file:

File Name	File Size
1-7SN1D.ps	184 KB

Installation Instructions:

1. Download 1-7SN1D 1.ps file via the Fiery Downloader, Web Downloader or use the import function of CWS 4.x to import to the Print queue.
2. In Command Workstation/Spooler (web), verify that 1-7SN1D.ps is in the printed queue.
3. Wait 60 seconds.
- 4a. On a Fiery with FACI interface kit, choose Start, Shut down, Restart, and go to step 5.
- 4b. On a Fiery without FACI interface kit, press the menu button under the LCD display, select Shut Down, and select Reboot System.
5. After the server has restarted, please wait until it goes to idle and print a Configuration Page to verify that the file has been received. The Update Information should contain the patch number 1-7SN1D.ps.