

DocuColor® 7002/8002

System Administration Guide



©2009 Xerox Corporation. All rights reserved. Xerox, Xerox Canada Ltd, Xerox Limited, and the sphere of connectivity design are trademarks of Xerox Corporation in the United States and/or other countries.

Changes are periodically made to this document. Changes, technical inaccuracies, and typographic errors will be corrected in subsequent editions.

Table of contents

1. Tools Mode	1-1
Overview	1-1
Entering and exiting Tools Mode	1-1
Navigating in Tools Mode	1-2
Machine Defaults	1-3
Machine Defaults 1	1-4
Initial Screen	1-4
NVM Read/Write	1-6
Special Media Setting for Drilled Papers	1-6
Special Media Setting for LEF Tab Stock	1-6
Carbonless Media Enablement	1-7
Tray Priority	1-9
System Timers	1-10
Power Saver	1-10
Screen Saver	1-11
Job Spacing	1-12
Tools Off	1-13
Auto Resume Print	1-14
Auto Resume Stop	1-15
Auto Resume Hold	1-16
Audio Tones	1-17
Productivity Setting	1-18
Single Paper Weight	1-18
Mixed Paper Weight	1-18
All Weights Rated Speed	1-18
Productivity charts	1-18
Single Paper Weight 19	
Mixed Paper Weight 20	
All Weights Rated Speed 21	
Productivity Setting procedure	1-22
Auto Tray Switching	1-23
Oversize Paper Offset	1-24
Set Date & Time	1-25
Setting the Date	1-25
Setting the Time	1-26
Dual Language	1-26
Non-Standard Paper Size	1-27
Machine Defaults 2	1-28
Decurler Adjustment	1-28
Custom Paper procedure	1-29
Access the Custom Paper Profile feature	1-29
Select the specific Paper Tray and Paper Type Switch options	1-30
Select Custom Paper Adjustment option	1-32
Select a Custom Paper Profile option	1-32

Base Range of Paper Type	1-34
2nd BTB.....	1-34
Decurler Penetration Amount	1-37
Aligner NIP Pressure	1-37
Air Assist Operation Selection	1-38
Select an Alignment Adjustment Profile (if necessary)	1-39
Load paper tray and run a Test Print.....	1-39
Alignment Adjustment Profile	1-41
Access the Alignment Adjustment feature	1-42
Select a paper tray and a profile number	1-43
Select an Alignment Profile button	1-44
Run a Test Print.....	1-44
Select an Alignment Adjustment feature	1-45
Lead Registration.....	1-45
Side Registration	1-46
Perpendicularity	1-46
Side Skew	1-47
FS Direction Image Magnification.....	1-48
SS Direction Image Magnification.....	1-49
Run more Test Prints.....	1-50
Deactivating an Alignment Adjustment Profile.....	1-51
Finishing System Module Profile (DFA device)	1-52
2. Auditor.	2-1
Overview.....	2-1
Initialization	2-2
Create/Modify User Accounts.....	2-3
Creating a User Account	2-3
Modifying a User Account	2-5
Changing the Tools Mode Password	2-5
Creating a Password for the Auditor Mode	2-6
Review Printer Job Account	2-7
3. Charts.	3-1
E Table Settings Chart: Type E1	3-1
E Table Settings Chart: Type E2.....	3-2
E Table Settings Chart: Type E3	3-3
E Table Settings Chart: Type E4	3-4
E Table Settings Chart: Type E5	3-5
E Table Settings Chart: Type E6	3-6
Custom Paper Setup Chart 1	3-7
Custom Paper Setup Chart 2	3-8
Custom Paper Setup Chart 3	3-9
Custom Paper Setup Chart 4	3-10
Alignment Adjustment Profile Chart 1	3-11
Alignment Adjustment Profile Chart 2	3-12
Alignment Adjustment Profile Chart 3	3-13
Alignment Adjustment Profile Chart 4	3-14

Tools Mode

1

Overview

The Tools Mode enables you to establish the default settings for your digital press to fit your individual requirements. You can change the settings for a variety of features, such as the initial screen to display when the press is powered on, the language to display on the Touch Screen, special paper sizes that can be used in the Paper Trays, timers, audio tone controls, default settings for scanner features, image quality settings, and more.

Entering and exiting Tools Mode


Tip

Keep the following in mind as you learn about the Tools Mode:

- If you attempt to access the Tools Mode while a job is printing, access to the Tools screens is delayed until the job completes the printing process.
- Jobs will queue, but will not print while the Tools Mode is active.
- You cannot access the Tools Mode if the digital press is in a Fault condition.
- You cannot access the Tools Mode if the Pause key on the Control Panel was pressed to halt a job. When the halted job completes the printing process, the Tools Mode may be accessed.

Use the following procedure to enter and exit the Tools Mode:

1. Press the **Access** button on the Control Panel. The *Access Password* Screen appears.



The screenshot shows a control panel screen with a black header bar containing the text "Please enter your Password. Follow the instructions on the Screen." Below this is a grey bar with the title "Access Password" and a "Cancel" button on the right. The main area of the screen is light grey and contains the instruction "Enter your password using the Numeric Keypad on the Control Panel, then press Enter." Below this instruction is a label "Password" above a white rectangular input field. Below the input field is a grey button labeled "Enter".


2. Use the keypad to enter the Tools Mode password.

The default password is five ones (**11111**).

For security reasons, only asterisks are displayed on the screen.

3. Touch the Enter button.

The Pathway Options screen appears.



Note

It is recommended that you change the Tools password as soon as possible after installing the digital press in order to prevent unauthorized access to the Tools Mode. The procedure for changing the password is in Chapter 2 of this manual.

4. Touch the **Tools Pathway** button on the screen; you are now in the Tools Mode.
5. To exit the Tools Mode, touch the **Exit Tools** button.

Navigating in Tools Mode

The following table tells you how to navigate in Tools Mode by touching buttons.



Button	Result
Tabs	Allows you to view the options available on that screen.
Enter	Saves any changes you made on the screen.
System Default	Returns the settings on the screen to the factory default settings.
Close	Closes the screen and returns the system to the previous screen.
Off	Deactivates the feature.
Reset	Returns the settings on the screen to the settings that were in effect when the screen opened.
Cancel	Cancels the changes made on the screen.
Exit Tools	Exits the Tools Mode.

Note

Changes made to default settings in the Tools Mode take effect when you exit Tools Mode.

Machine Defaults

Two *Machine Defaults* screens are available for changing default settings. Each of the features shown on the below screen is described throughout the remainder of this chapter.




Note

The Service Call feature is not available.

Machine Defaults 1

This section describes the default settings available to you on the *Machine Defaults 1* screen and include the following (as shown in the illustration):



The default settings procedures on the following pages are accessed from The *Machine Defaults 1* screen.

Note

The D-MAX Setup feature may or may not be selectable with your DocuColor 7002/8002 Digital Press configuration. In either case, this feature is for the Xerox Service Representative **only** and is not for customer use.

Initial Screen

Use the Initial Screen to select the screen that displays when the digital press is powered on. You can choose from two screens:


- Job Status
- Machine Status

Note

The *Machine Status* screen is the factory default setting.


Use the following procedure to change the default initial screen.

1. Touch the **Initial Screen** button on the *Machine Defaults 1* screen. The *Initial Screen* screen appears.



2. Touch the **Machine Status** or **Job Status** button.

If you select the Machine Defaults screen, the screen below appears when the machine is powered on.



If you change the default setting to the Job Status screen, the screen below appears when the machine is powered on. This screen displays all the jobs currently queued for printing.

Ready to Print.

Job List	Hold Job	Release Job	Promote Job	Delete Job	Job Details
1 Network Print: Printing					8.5x11.0" Quantity: 1 Pages: 4
2 Network Print: Queued					11.0x17.0" Quantity: 6 Pages: 2
3 Network Print: Queued					8.5x11.0" Quantity: 50 Pages: 8
4 Network Print: Queued					8.5x11.0" Quantity: 10 Pages: 25

1/1

Note

Refer to the User Guide for more information about the Machine Status and Job Status screens.

NVM Read/Write

Your Xerox service representative uses this feature to change certain system settings. It also may occasionally be used by system administrators.

Tools Mode.
Use the Keypad to input at Chain-Link number, then press start.

Tools Mode:
Non-Volatile Memory Read / Write

Chain Link Number

Current Value

New Value

Press Start to replace the current Non-Volatile Memory value with the new Non-Volatile Memory value.

Input Chain Link

Under most conditions, this feature is not used by system administrators; however, there are limited circumstances under which this feature is used. These circumstances include:

Special Media Setting for Drilled Papers

If you use 3-hole, predrilled paper on a regular basis and continually encounter an inordinate amount of paper jams, and/or

Special Media Setting for LEF Tab Stock

If you regularly run tab stock and continually encounter paper jams.

Carbonless Media Enablement

- Carbonless papers are coated with several functional coatings which promote the image transfer through the form set and enable the form sets to separate appropriately after padding with a special adhesive. Each supplier of xerographic carbonless paper has developed their own unique chemistry, which is why the following procedure enabling this application, works best with Xerox Premium Digital Carbonless Paper.
- In order to avoid problems when running carbonless media, you may use the NVM Read/Write feature to switch on the carbonless media feature.

If any of the above conditions exist in your environment, you may use the NVM Read/Write feature to switch on a feature.

! CAUTION

Do not enter any numbers on this screen other than the ones described in this procedure. Entering and saving numbers, other than the ones described, changes the system settings which may result in a service call to restore the system to the correct settings.

To switch **on** a feature, perform the following:

- From the NVM Read/Write screen, use the keypad on the Control Panel and enter the **Chain Link Number**:
 - The Chain Link Number for Special Media Setting for Drilled Papers is **700 545**.
 - The Chain Link Number for Special Media Setting for LEF Tab Stock is **700 546**.
 - The Chain Link Number for Carbonless Media Enablement is **700-920**.

Note

For the purpose of this procedure, the following screens show the Chain Link Number, Current Value, and New Value for Special Media Setting for Drilled Papers. The Current Value and New Value numbers will vary depending on the Chain Link Number entered.

- After entering the desired Chain Link Number, press the **Start** button on the Control Panel. The UI displays this screen:

Tools Mode.
Use the Keypad to input at Chain-Link number, then press start.

Tools Mode:
Non-Volatile Memory Read / Write

Chain Link Number: 700-545

Current Value: 1000

New Value:

Press Start to replace the current Non-Volatile Memory value with the new Non-Volatile Memory value.

Input Chain Link

Close

3. To switch **on** a feature, press the appropriate button on the Control Panel keypad:
 - For Special Media Setting for Drilled Papers, press **0**.
 - For Special Media Setting for LEF Tab Stock, press **1**.
 - For Carbonless Media, press **1**.
4. After entering the New Value number, press the **Start** button. The UI displays the following screen:

Tools Mode.
Use the Keypad to input at Chain-Link number, then press start.

Tools Mode:
Non-Volatile Memory Read / Write

Chain Link Number: 700-545

Current Value: 1000

New Value: 0

Press Start to replace the current Non-Volatile Memory value with the new Non-Volatile Memory value.

Input Chain Link

Close

5. Touch the **Close** button to save and close your new setting.
6. Exit Tools Mode and run your print job.

Tip

After running your print job, reenter Tools Mode, NVM Read/Write, and **switch off** the feature that is currently on. Follow the steps outlined in this procedure and use these settings for the New Value number:

- To switch off the Special Media Setting for Drilled Papers, enter **1000**.
- To switch off the Special Media Setting for LEF Tab Stock, enter **0**.
- To switch off the Carbonless Media, enter **0**.

Tip


To prevent paper jams from occurring with stock types other than the ones mentioned in this procedure, you **must switch off** the NVM Read/Write feature **before** running other print jobs.

Tray Priority

Select the priority order for each paper tray. If the Auto Tray Switching feature is enabled and each paper tray contains the same paper size and weight, the digital press feeds paper from the tray set at Priority 1. If there is no paper in the Priority 1 tray, the Priority 2 tray is automatically selected and so on.

Use the following procedure to set the priority for each paper tray.

1. Touch the **Tray Priority** button on the *Machine Defaults 1* screen. The Tray Priority screen appears.




2. Touch the desired Priority button in the Priority column.
3. Touch the button for the Paper Tray that will have that priority. The number of the selected Paper Tray appears next to that Priority button.
4. Repeat this procedure for each Priority. You cannot set the same paper tray for more than one Priority at a time.
5. Touch the **Close** button to return to the *Machine Defaults 1* screen. You cannot touch the Close button until you set paper trays for each Priority.

System Timers

Use this feature to change the factory default settings for the timers in the digital press. To access the various timers, touch the **System Timers** button on the *Machine Defaults 1* screen.

The *System Timers* screen appears. From this screen you can view the time currently set for each of the timers, and select the one you want to change.




Power Saver

Use this feature to set the time that elapses until the digital press enters a reduced power consumption mode. This timer is activated when all print jobs have been completed and there are no jobs in the job queue.

The digital press exits the Power Saver mode when a job is sent to be printed or the Touch Screen is activated.

1. Touch the **Power Saver** button on the *System Timers* screen.



2. Use the up or down arrow buttons to change the time. The range available is one to 240 minutes.


To use the system default time of fifteen minutes, touch the **System Default** button.

3. Touch the **Enter** button on the screen to enter the new time into the system.
4. Touch the **Close** button to return to the *Machine Defaults 1* screen or to select another timer to change.

Screen Saver

The Screen Saver feature allows you to protect the screen from being damaged with permanent marks if the digital press is idle for a period of time.

1. Touch the **Screen Saver** button on the *System Timers* screen.



2. Use the up or down arrow buttons to change the time. The range available is ten to sixty minutes.


To use the system default time of ten minutes, touch the **System Default** button.

3. Touch the **Enter** button on the screen to enter the new time into the system.
4. Touch the **Close** button to return to the *Machine Defaults 1* screen or select another timer to change.

Job Spacing

Use the Job Spacing feature when there are multiple jobs queued and you would like to allow seven seconds to unload prints from a finishing device before the next job starts printing.

1. Touch the **Job Spacing** button on the *System Timers* screen.



2. Touch the **7 Seconds** button to enable the feature or touch the **Off** button to disable the feature.
3. Touch the **Close** button to return to the *Machine Defaults 1* screen or select another timer to change.


Tools Off

Use the Tools Off feature to have the digital press automatically return to the printing mode when no action is taken on the Tools Mode screens after the set amount of time.

Tip

Jobs sent over the network will queue but will not print while the Tools Mode is active.

1. Touch the **Tools Off** button on the *System Timers* screen.



2. Use the up or down arrow buttons to change the time. The range available is ten to sixty minutes.


To use the system default time of ten minutes, touch the **System Default** button.

3. Touch the **Enter** button on the screen to enter the new time into the system.
4. Touch the **Close** button to return to the *Machine Defaults 1* screen or select another timer to change.

Auto Resume Print

Use the Auto Resume Print feature to restart a job automatically after a fault is cleared and a job received over the network is waiting for user instruction.

1. Touch the **Auto Resume Print** button on the *System Timers* screen.



2. Use the up or down arrow buttons to change the time. The range available is one to ten minutes.


To use the system default time of two minutes, touch the **System Default** button.

3. Touch the **Enter** button on the screen to enter the new time into the system.
4. Touch the **Close** button to return to the *Machine Defaults 1* screen or select another timer to change.

Auto Resume Stop

Use the Auto Resume Stop feature to restart a job automatically after the Pause button on the Control Panel is pressed and the job is waiting for user instruction.

1. Touch the **Auto Resume Stop** button on the *System Timers* screen.



2. Use the up or down arrow buttons to change the time. The range available is one to ten minutes.


To use the system default time of two minutes, touch the **System Default** button.

3. Touch the **Enter** button on the screen to enter the new time into the system.
4. Touch the **Close** button to return to the *Machine Defaults 1* screen or select another timer to change.

Auto Resume Hold

Use the Auto Resume Hold feature to automatically print the next job in the queue if the current job is waiting for user instruction to clear a certain type of fault.

1. Touch the **Auto Resume Hold** button on the *System Timers* screen.



2. Use the up or down arrow buttons to change the time. The range available is one to ten minutes.

To use the system default time of two minutes, touch the **System Default** button.

3. Touch the **Enter** button on the screen to enter the new time into the system.
4. Touch the **Close** button to return to the *Machine Defaults 1* screen or select another timer to change.


Audio Tones

There are three types of audio tones that can be activated on the digital press, as shown in the following table.

Tone	What the Tone Indicates
Attention Tone	An unselectable button has been touched.
Button Selection Tone	A selectable button has been touched.
Fault Tone	The press is in a fault condition and cannot continue printing.

Each of these tones can be deactivated or set to Soft, Normal, or Loud. The factory default setting is Normal.

1. Touch the **Audio Tones** button on the *Machine Defaults 1* screen.




2. Touch the button for the desired volume setting for each tone. To deactivate a tone, touch the **Off** button for that tone.
3. Touch the **Reset** button to restore the factory default setting for the three tones.
4. Touch the **Close** button to return to the *Machine Defaults 1* screen.

Productivity Setting

The productivity of the digital press relates to the continuous speed of the media output as measured in prints per minute (ppm). The continuous speed is dependent on paper size, paper weight, and fuser temperature.

Use this setting to optimize the throughput speed for the type of paper you run most frequently. Productivity Setting options are shown and explained in the following illustration:



Single Paper Weight

This setting optimizes the throughput speed for light weight or heavy weight papers, according to the weight range that is set in the paper tray.

Mixed Paper Weight

This setting optimizes the throughput speed of print jobs that contain mixed media weights from different paper trays.

All Weights Rated Speed

This setting allows all print jobs to run at the same, or rated, throughput speed, regardless of weight. The digital press produces/prints images with a reduced level of gloss on the output.

Productivity charts

The following productivity charts lists the various paper weights and sizes and their related print speeds for 1 Sided and 2 Sided output. Each chart outlines the print speed parameters for both productivity settings.

Single Paper Weight

Single Paper Weight Mode						
Paper Weight	Paper Size(Feed direction length)[mm]		Print Speed for DocuColor 8002		Print Speed for DocuColor 7002	
	Min.	Max	1 Sided	2 Sided	1 Sided	2 Sided
60 - 80 g/m ²	182.0	216.0	80	40	70	35
	216.1	297.0	60	30	60	30
	297.1	458.0	40	20	35	17.5
	458.1	488.0	30	15	30	15
81 - 105 g/m ²	182.0	216.0	80	40	70	35
	216.1	297.0	60	30	60	30
	297.1	458.0	40	20	35	17.5
	458.1	488.0	30	15	30	15
106 - 135 g/m ²	182.0	216.0	80	40	70	35
	216.1	297.0	60	30	60	30
	297.1	458.0	40	20	35	17.5
	458.1	488.0	30	15	30	15
136 - 186 g/m ²	182.0	216.0	60	30	50	25
	216.1	450.0	30	15	25	12.5
	450.1	488.0	20	10	15	7.5
187 - 220 g/m ²	182.0	216.0	60	30	50	25
	216.1	450.0	30	15	25	12.5
	450.1	488.0	20	10	15	7.5
221 - 300 g/m ²	182.0	216.0	40	20	35	17.5
	216.1	280.0	30	15	30	15
	280.1	458.0	20	10	15	7.5
	458.1	488.0	10	5	10	5
Transparency	210.0	216.0	30	-	30	-

Notes

- 2-Sided printing is not available for transparency and paper that is 221 g/m² or greater.
- There is no decrease in productivity (ppm) from the second feeder module to the first feeder module.
- Transparency is only available for 1 Sided, A4 or 8.5 in. x 11 in.LEF.

Mixed Paper Weight

Mixed Paper Weight Mode						
Paper Weight	Paper Size(Feed direction length)[mm]		Print Speed for DocuColor 8002		Print Speed for DocuColor 7002	
	Min.	Max	Simplex	Duplex	Simplex	Duplex
60 - 80 g/m ²	182.0	216.0	80	40	70	35
	216.1	297.0	60	30	60	30
	297.1	458.0	40	20	35	17.5
	458.1	488.0	30	15	30	15
81 - 105 g/m ²	182.0	216.0	80	40	70	35
	216.1	297.0	60	30	60	30
	297.1	458.0	40	20	35	17.5
	458.1	488.0	30	15	30	15
106 - 135 g/m ²	182.0	216.0	60	30	60	30
	216.1	450.0	30	15	30	15
	450.1	488.0	20	10	20	10
136 - 186 g/m ²	182.0	216.0	60	30	50	25
	216.1	450.0	30	15	25	12.5
	450.1	488.0	20	10	15	7.5
187 - 220 g/m ²	182.0	216.0	40	20	40	20
	216.1	280.0	30	15	30	15
	280.1	458.0	20	10	20	10
	458.1	488.0	10	5	10	5
221 - 300 g/m ²	182.0	216.0	40	20	35	17.5
	216.1	280.0	30	15	30	15
	280.1	458.0	20	10	15	10
	458.1	488.0	10	5	10	5
Transparency	210.0	216.0	30	--	30	--

Notes

- 2-Sided printing is not available for transparency and paper that is 221 g/m² or greater.
- There is no decrease in productivity (ppm) from the second feeder module to the first feeder module.
- Transparency is only available for 1 Sided, A4 or 8.5 in. x 11 in.LEF.

All Weights Rated Speed

All Weights Rated Speed Mode						
Paper Weight	Paper Size (Feed direction length) [mm]		Print Speed for DocuColor 8002 (prints per minute)		Print Speed for DocuColor 7002 (prints per minute)	
	Min.	Max	1 Sided	2 Sided	1 Sided	2 Sided
60 - 80 g/m ²	182.0 mm	216.0 mm	80	40	70	35
	216.1 mm	297.0 mm	60	30	60	30
	297.1 mm	458.0 mm	40	20	35	17.5
	458.1 mm	488.0 mm	30	15	30	15
81 - 105 g/m ²	182.0 mm	216.0 mm	80	40	70	35
	216.1 mm	297.0 mm	60	30	60	30
	297.1 mm	458.0 mm	40	20	35	17.5
	458.1 mm	488.0 mm	30	15	30	15
106 - 135 g/m ²	182.0 mm	216.0 mm	80	40	70	35
	216.1 mm	297.0 mm	60	30	60	30
	297.1 mm	458.0 mm	40	20	35	17.5
	458.1 mm	488.0 mm	30	15	30	15
136 - 186 g/m ²	182.0 mm	216.0 mm	80	40	70	35
	216.1 mm	297.0 mm	60	30	60	30
	297.1 mm	458.0 mm	40	20	35	17.5
	458.1 mm	488.0 mm	30	15	30	15
187 - 220 g/m ²	182.0 mm	216.0 mm	80	40	70	35
	216.1 mm	297.0 mm	60	30	60	30
	297.1 mm	458.0 mm	40	20	35	17.5
	458.1 mm	488.0 mm	30	15	30	15
221 - 300 g/m ²	182.0 mm	216.0 mm	80	40	70	35
	216.1 mm	297.0 mm	60	30	60	30
	297.1 mm	458.0 mm	40	20	35	17.5
	458.1 mm	488.0 mm	30	15	30	15
Transparency (Only available for 1-Sided, 8.5 x 11 inch/A4 LEF)	210.0 mm	216.0 mm	30	-	30	-


Notes

- 2-Sided printing is not available for transparency and paper that is 221 g/m² or greater.
- There is no decrease in productivity (ppm) from the second feeder module to the first feeder module.
- Transparency is only available for 1 Sided, A4 or 8.5 in. x 11 in.LEF.


Productivity Setting procedure

Use the following procedure for choosing the setting which is best for your environment.

1. Touch the **Productivity Setting** button on the *Machine Defaults 1* screen.



2. Select the button for the type of paper you use most frequently in the digital press, either **Single Paper Weight**, **Mixed Paper Weight**, or **All Weights Rated Speed**.




3. Touch **Close** to return to the *Machine Defaults 1* screen.

Auto Tray Switching

This feature allows you to set the default settings for the following options:

Default Setting	What the Default Does
Auto Tray Switching (ATS)	Allows the digital press to automatically select another paper tray, containing the appropriate paper, if the selected paper tray becomes unusable
Auto Paper Selection (APS)	Allows the digital press to automatically select the appropriate paper size for the job being processed, without a specific paper tray being selected
Inhibited Tray	Allows you to select a specific paper tray, or trays, that you want the digital press to bypass, regardless of the Tray Priority settings

1. Touch the **Auto Tray Switching** button on the *Machine Defaults 1* screen.



2. Touch the **Enable** or **Disable** button for the Auto Tray Switching option.
3. Touch the **Enable** or **Disable** button for the Auto Paper Selection option.
4. To instruct the digital press to bypass one or more of the paper trays, touch the desired Paper Tray button in the Inhibited Tray column.
 - To deselect a paper tray, touch that Paper Tray button again.
 - To return the settings to the last saved values, touch the **Reset** button.
5. Touch the **Close** button to return to the *Machine Defaults 1* screen.

Oversize Paper Offset


Use this feature for media that is larger than long edge feed, 8.5x11 inch/A4 paper, such as 12 x 18 in. (304.8 x 457.2 mm).

Note

Some color server manufacturers have an oversize paper offset feature that you can also use to adjust the position of the image on the paper. Refer to the documentation that came with your color server.

Use the following procedure to adjust the registration on paper that is larger than 8.5 x 11 in./A4.

1. Select the **Oversize Paper Offset** feature.
2. From the **Oversize Paper Offset** screen, select the desired **Oversize Paper Offset** button to adjust the registration on paper larger than 8.5x11 inch or A4 LEF.




The table on the following page defines each offset level.

3. Touch the **Offset Level 1, 2, 3, or 4** button to adjust the position of the paper as it feeds. Refer to the following table for the adjustments made for each Offset Level.

Paper Size	Level 1	Level 2	Level 3	Level 4
310mm	10.0mm	10.0mm	10.0mm	10.0mm
311mm	9.5mm	9.5mm	9.5mm	9.5mm
312mm	9.0mm	9.0mm	9.0mm	9.0mm
313mm	8.5mm	8.5mm	8.5mm	8.5mm
314mm	8.0mm	8.0mm	8.0mm	8.0mm
315mm	7.5mm	7.5mm	7.5mm	8.0mm
316mm	7.0mm	7.0mm	7.0mm	8.0mm
317mm	6.5mm	6.5mm	7.0mm	8.0mm
318mm	6.0mm	6.0mm	7.0mm	8.0mm
319mm	5.5mm	6.0mm	7.0mm	8.0mm
320mm	5.0mm	6.0mm	7.0mm	8.0mm

The following illustration demonstrates how the image is shifted on the paper after selecting an Oversize Paper Offset level.




Set Date & Time

Use this feature to set the date and time for the system. The date and time is displayed on the *Error Log* screen and on the *Date and Time* screens.

Setting the Date

1. Touch the **Set Date & Time** button on the *Machine Defaults 1* screen. The *Set Date and Time* screen appears with the Set Date button selected and options for setting the date displayed on the right.




2. Select the date format you wish to use.
3. Use the up or down arrow buttons to enter the correct year, month, and day.
4. Touch the **Enter** button on the screen to save your selections.

The next time you enter the Tools Mode, the date that you set is displayed.

Setting the Time

1. Touch the **Set Date & Time** button on the *Machine Defaults 1* screen. The *Set Date and Time* screen appears with the Set Date button selected and options for setting the date displayed on the right.
2. Touch the **Set Time** button. Options for setting the time appear in the Set Time screen.



3. Touch the **12 Hour Clock** or the **24 Hour Clock** button.
4. Use the up or down arrow buttons to set the correct hour and minutes.

If you selected the 12 Hour Clock, touch the **AM** or **PM** button.

5. Touch the **Enter** button on the screen to save your selections.

The next time you enter the Tools Mode, the time that you set will be displayed.

6. Touch the **Close** button to return to the *Machine Defaults 1* screen.


Dual Language

This feature enables you to set one of two available languages as the default for the Touch Screen. When your digital press was installed, your Xerox service representative loaded onto your system your choice of two languages that you can choose from to be displayed on the Touch Screen.

1. Touch the **Dual Language** button on the *Machine Defaults 1* screen.
2. Touch the button for the default language you want to appear on the Touch Screen.

After exiting the Tools Mode, you can switch the Touch Screen to the other language by pressing the **Dual Language** button on the Control Panel.

3. Touch the **Close** button to return to the *Machine Defaults 1* screen.




Non-Standard Paper Size

You can run non-standard sized paper from any paper tray by entering the paper size on the Non-Standard Paper Size screen for the tray being used.

Tip

Be sure to select Non-Standard Size on the top front of the tray, and use the Paper Weight Indicator at the right side of the tray to select the paper weight being used.


1. Touch the **Non-Standard Size Paper** button on the *Machine Defaults 1* screen.




2. Touch the desired Paper Tray button on the *Non-Standard Paper Size* screen.
3. Use the up or down arrow buttons on the screen to enter the X and Y dimensions of the paper being used in the tray. The dimensions shown on the screen above the X and Y boxes indicate the minimum and maximum sizes you can enter.
4. Touch the **Close** button to return to the *Machine Defaults 1* screen.
5. To use these settings, exit the Tools Mode and ensure that **Non-Standard Size** has been selected on the top/front of the tray.

Machine Defaults 2

This section describes the features available to you through the *Machine Defaults 2* screen. Select the **Machine Defaults 2** tab, and one of the following screens appears.



If your system has an optional finishing device attached, this screen may reflect a finishing device option as shown below:



Use the procedures on the following pages to make default settings for the available features.

Decurler Adjustment

For information on the Decurler and the step-by-step instructions on using it, refer to the document entitled **DocuColor 8002/7002 Decurler Adjustment**.

Custom Paper procedure


Use the following procedure for creating/modifying a Custom Paper Profile.

Tip


Before creating or modifying Custom Paper Profiles, copy and use the chart at the back of this book to record your Custom Paper Profile settings. This will ensure that you select the correct profile for a custom job.

Access the Custom Paper Profile feature

1. Select the **Custom Paper Profile** feature from **Machine Defaults 2**.



2. The **Custom Paper Setup** window opens.



Select the specific Paper Tray and Paper Type Switch options

3. Select the specific **Paper Tray** for which the Custom Paper Profile will be created. If you have a SFM attached, this screen reflects the additional Paper Trays 3 and 4.
4. Select the **Paper Type Switch**.

Tools Mode.

Tools Mode:
Custom Paper Setup

Reset Close

Paper Tray

1
2

Paper Type Switch

Off Transparency

60-80 g/m² Uncoated 60-80 g/m² Coated

81-105 g/m² Uncoated 81-105 g/m² Coated

106-135 g/m² Uncoated 106-135 g/m² Coated

136-186 g/m² Uncoated 136-186 g/m² Coated

187-220 g/m² Uncoated 187-220 g/m² Coated

221-300 g/m² Uncoated 221-300 g/m² Coated

Custom Paper Assignment

Custom Paper Adjustment

Custom Profile 1

Paper Type: 81-105 g/m² Uncoated

Alignment Profile: 1

Note

The default setting is **Off**.

- The Paper Type Switches correspond with the media buttons/switches on the paper trays:

Paper Size		Paper Weight (g/m ²)							Paper Type	
Non-Standard	Standard	Transparency	60 - 80	81 - 105	106 - 135	136 - 186	187 - 220	221 - 300	Coated	Uncoated
<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>


- Selecting a Paper Type Switch informs the digital press that custom paper is loaded in the tray and to use the corresponding Custom Paper Profile when those buttons/switches are selected on the specified paper tray.

Refer to the following example:

Tip

This is an example only. Do **not** perform these steps at this time.

1. The Paper Type Switch corresponds with the selections on the paper tray.




4. The digital press will use the assigned Custom Paper Profile when running the print job.

Tip


The Paper Type Switch does **not** have to match the actual type of paper you are loading in the tray. When creating a Custom Paper Profile, select a Paper Type that is rarely or never used as your Paper Type Switch. This ensures that when running commonly used paper types, the digital press does not load a Custom Paper Profile for those types.

Select Custom Paper Adjustment option

5. Select Custom Paper Adjustment.



The Custom Paper Adjustment window opens.



Select a Custom Paper Profile option

6. Select a Custom Paper Profile button.


- After selecting a Custom Paper Profile button, the Custom Paper Profile and Alignment Adjustment buttons on the right are selectable.

Tip


Important information about this feature includes the following:

- You can create and store up to ten different Custom Paper Profiles.
- Only one custom profile is enabled for each tray.
- If you create and store multiple profiles for a specific tray, ensure that you select the desired profile (1-10) you want to use for that tray before exiting Tools. That Custom Paper Profile is reflected on the Machine Status screen.

7. From the **Modify/Review** area, select the Custom Paper Profile button.



The **Custom Paper Profile** window opens.




These options allow you to further “fine-tune” your custom paper profile and are explained in more detail on the following pages.

These options include:


Base Range of Paper Type

- This is the **actual** type of paper you are loading in the paper tray.



2nd BTB


- The Second Bias Transfer Belt is a feature that is normally used with heavier weight paper (220 g/m² and greater, 10 pt, 12 pt).



- The default settings for **2nd BTB Side 1** and **Side 2** are both **100%**.
- Adjust Side 1 for all simplex jobs. If defects remain in a printed job, perform the following steps to determine if Side 1 or Side 2 adjustments are appropriate.
 - If the job is face down or 1-N, use Side 1 for defects on the topside of the stacked sheets, and use Side 2 for the downside.
 - If the job is face up or N-1, use Side 2 for defects on the topside of the stacked sheets, and use Side 1 for the downside.


Use This feature when your:

- a. Prints may have mottle, which is uneven spotty toner coverage that occurs when printing large, solid areas of flat color (refer to the below illustration)




If mottle exists and it is heavy weight paper, **increase** one or both of the 2nd BTB values.

If mottle exists and it is light weight paper, **increase** one or both of the 2nd BTB values. Evaluate the image quality. If the image quality is equal to or worse than the 100 % default setting, decrease one or both of the 2nd BTB values until a satisfactory image quality is obtained.




- b. Prints have a color shift where the colors are much different than what you desire (refer to the below illustration).



This test pattern represents an output with the desired colors.


This test pattern represents an output with a shift in colors, and thereby an undesired output.

If mottle color shift exits, increase one or both of the 2nd BTB values.



Decurler Penetration Amount


- Use this feature to compensate for paper curl in your output prints. This is the same as the Decurler Setup feature.



For specific Decurler information, refer to the Decurler Setup and Decurler E Table Settings section earlier in this chapter.

Aligner NIP Pressure

- Use this feature with paper types that slip and skew or have damaged edges.



Examples:


- Some coated paper types slip and skew, thereby having the image misregistered on the output prints. In this case, you may want to increase the NIP pressure in order to compensate for the slippage and skewing.
- Some light-weight papers may have too much NIP pressure applied to them, thereby causing edge damage to the output prints. In this case, you may to decrease the NIP pressure.
- If you are experiencing numerous 8-154 faults, increase the NIP pressure and continue to run the digital press.

Tip

Increasing the NIP pressure for numerous 8-154 faults, allows you to postpone a service call. However, call your service representative as soon as possible in order to restore the digital press to its full feeding capabilities.

Air Assist Operation Selection

- Use this feature to switch on or switch off the fans in a paper tray in order to eliminate misfeeds, paper jams, or other possible tray feeding problems. You can also select Auto if you want the digital press to decide whether or not to switch on or off the fans for a paper tray.

**Note**


The default setting is Auto.

Examples:

- If the digital press is producing multifeeds, try setting this option to **Operate (On)** instead of Auto.
 - If your output contains two sheets that are stuck together, try setting this option to **Operate (On)**.
 - If misfeeds are occurring (the paper is not leaving the tray) and the environment is too dry, try setting this option to **Do Not Operate (Off)** instead of Auto.
8. Make the desired selections from the Custom Paper Profile selections. Select **Close** to save the changes and close the window.

Select an Alignment Adjustment Profile (if necessary)

9. If necessary, you can select or create an Alignment Adjustment Profile for this Custom Paper Profile.




Note

For information on the Alignment Adjustment feature refer to the section later in this chapter entitled Alignment Adjustment.

Load paper tray and run a Test Print

10. Load your custom paper in the same paper tray as the one you selected for this Custom Paper Profile. **Ensure that you set the tray buttons to reflect the same information as your Paper Type Switch settings.**
11. After you select all the desired settings for this Custom Paper Profile, run a **Test Print** to ensure that the output is satisfactory.



12. If the output is not satisfactory, perform Steps 1-10 again to readjust the parameters for this Custom Paper Profile.
 - Run another Test Print to ensure that your output is satisfactory.
 - Continue to perform these steps until your output is satisfactory.

13. Once your output is satisfactory, select the **Close** button.

This returns you to the Custom Paper Adjustment screen:

The screenshot shows the 'Tools Mode' window with the 'Custom Paper Adjustment' screen active. The window has a title bar 'Tools Mode.' and a menu bar 'Tools Mode: Custom Paper Adjustment' with a 'Close' button. The main area is divided into three sections: 'Custom Paper Profile' on the left, 'Modify / Review' on the right, and a central area for profile selection. The 'Custom Paper Profile' section contains two columns of buttons labeled 'Custom Profile 1' through 'Custom Profile 10'. The 'Modify / Review' section contains two radio buttons: 'Custom Paper Profile 1' (selected) and 'Alignment Adjustment'. Below the 'Custom Paper Profile 1' radio button, the text 'Paper Type: 81-105 g/m² Uncoated' is displayed. Below the 'Alignment Adjustment' radio button, the text 'Alignment Profile: 1' is displayed.


14. Select the **Close** button to return to the Custom Paper Setup screen:

The screenshot shows the 'Tools Mode' window with the 'Custom Paper Setup' screen active. The window has a title bar 'Tools Mode.' and a menu bar 'Tools Mode: Custom Paper Setup' with 'Reset' and 'Close' buttons. The main area is divided into three sections: 'Paper Tray' on the left, 'Paper Type Switch' in the center, and 'Custom Paper Assignment' on the right. The 'Paper Tray' section contains two buttons labeled '1' and '2'. The 'Paper Type Switch' section contains two columns of buttons labeled 'Off', '60-80 g/m² Uncoated', '81-105 g/m² Uncoated', '106-135 g/m² Uncoated', '136-186 g/m² Uncoated', '187-220 g/m² Uncoated', and '221-300 g/m² Uncoated'. The 'Custom Paper Assignment' section contains a radio button labeled 'Custom Paper Adjustment' (selected) and a text area labeled 'Custom Profile 1' with 'Paper Type: 81-105 g/m² Uncoated' and 'Alignment Profile: 1'.

15. Select the **Close** button to save and close these settings for this Custom Paper Profile.

If you do not want to save this profile, select the **Reset** button to discard all the selections for this profile and reset them to the machine defaults.

16. Close out of Tools Mode and return to the Machine Status screen. The Machine Status screen now displays your new Custom Paper Profile:



17. To switch off the Custom Paper Profile without going into or deleting it in Tools Mode, simply open the paper tray and select different paper type information (weight, coating, etc.) by changing the tray buttons/switches.

You can return to this saved Custom Paper Profile any time by changing the tray buttons/switches to reflect the desired profile.

Alignment Adjustment Profile

When printing duplex jobs and using different media types (including paper type, weight, and coating/uncoating), the output may require specific handling by the digital press as it is moving through the paper path. With certain media types and duplex jobs, the images on Side 1 and/or Side 2 may be misregistered, skewed, perpendicularly misaligned, or stretched.

As with the Custom Paper Setup feature, Alignment Adjustment feature allows you to create and store a maximum of twenty different Alignment Adjustment Profiles. These profiles allow you to accommodate different media types and how the image is registered, aligned, or magnified for Side 1 and Side 2 output. These profiles may be used at point of need in order to ensure optimum output quality of your print.

Note

You can create Alignment Profiles without associating them to a specific Custom Paper Profile. The reverse is also true: You can create an Alignment Profile and associate it to a specific Custom Paper Profile. For example, Custom Paper Profile 2 may be affiliated with Alignment Profile 2, so that when Custom Paper Profile 2 is in use, so is Alignment Profile 2.

When creating Alignment Profiles for Side 1 and/or Side 2 prints, be aware of the following:

- Side 1/Side 2 images may be misregistered because the paper is not the exact same size. It may vary slightly, with differences of plus or minus 1mm, causing the image to be misregistered. To reduce the possibility of size differences, it is recommended that you use paper from the same lot when running duplex jobs.
- During the fusing process, the heat and pressure applied to the paper causes the paper to stretch. If the images on Sides 1 and 2 are the same size, the stretching of the paper may cause the image on Side 1 to be slightly larger than the image on Side 2.
- Creating an Alignment Profile for these types of jobs allows you to reduce or eliminate the images being larger on Side1 than on Side 2 prints.

Notes

- Remember: Your Alignment Profile may or may not be affiliated with a Custom Paper Profile.
- Once an Alignment Profile is set and in use, your color server will not reflect that profile in the print options for print jobs.
- After an Alignment Profile is set, it remains active until you reenter Tools Mode and switch it off. If an active Alignment Profile is not associated with a Custom Paper Profile, it is used for each paper tray to which it is assigned.

Access the Alignment Adjustment feature

Use the following procedure to create/modify an Alignment Profile for adjusting Side 1/Side 2 image output.


Tip

Before creating or modifying Alignment Profiles, copy and use the chart at the back of this book to record your Alignment Profile settings. This will ensure that you select the correct profile for a custom job.

Note


If you require a Custom Paper Profile associated with this Alignment Profile, you can set the Custom Paper Profile information either now or after you create the Alignment Profile.

1. Access Tools Mode and touch the **Alignment Adjustment** button on the *Machine Defaults* 2 screen; the following window opens.



Select a paper tray and a profile number

2. Select a **Paper Tray**.




Tip

If you are creating an Alignment Profile in affiliation with a Custom Paper Profile and have arrived here from the Custom Paper Setup procedure, then this screen will not reflect any Paper Tray information. The Paper Tray information was selected earlier in your associated Custom Paper Profile.

Note

If you have an optional SFM attached to your digital press, this screen will reflect the additional Paper Trays 3 and 4.


3. Select a Profile number from 1-20 by touching the desired button.



The **Modify/Review** button is now selectable, as shown above.


Select an Alignment Profile button

4. Touch one of the **Alignment Profile** buttons; the Alignment Profile window opens.



Run a Test Print

5. Touch the **Test Print** button; a new window opens.



- a. Touch the **2 Sided** button.

Note


If you want to check the registration for 1 Sided prints only, touch the 1 Sided button.

- b. Select **10** test prints by touching the **Up** arrow button to change the number of test prints generated.
- c. Touch the **Pattern Generator** button.
- d. Retrieve your output test prints from the digital press.
- e. Discard the first few prints, as inconsistency tends to be greater with these images.

6. Evaluate the test prints by holding your 2 Sided output at eye level near a light source. This will allow you to see the registration marks for both Side 1 and Side 2 of the output.
 - a. If you determine that the registration between Side 1 and Side 2 is significant and needs adjusting, proceed to the Step 7.
 - b. If the registration between Side 1 and Side 2 is okay, stop now:
 - Touch the Close button to return to the Alignment Profile window.
 - Ensure that the Default button is selected and touch the Close button.
 - Exit Tools Mode.

Select an Alignment Adjustment feature


7. Select the desired Alignment feature that you want to adjust.



Each of the above Alignment features is discussed on the following pages.

Lead Registration


- Use this feature to adjust the lead edge of the image for Side 1 and/or Side 2 registration.



- The factory default setting is zero (0).
- The arrows on the right side of the illustration show the paper feed direction.
- The + sign, the left-pointing arrow, and the red lines shows the direction the image will move on the paper when the value is increased.
- If you select a negative value (for example, -1.0 mm), the image on the paper moves toward the right.

Side Registration


- Use this feature to adjust the side edge of the image for Side 1 and/or Side 2 registration.



- The factory default setting is zero (0).
- The + sign, the up arrow, and the red lines shows the direction the image will move on the paper when the value is increased.
- If you select a negative value (for example, -1.0 mm), the image on the paper moves downward.

Perpendicularity


- Use this feature to adjust the image digitally on the drum so that it will align with the paper for both Side 1 and Side 2.



- The factory default setting is zero (0).
- The arrows on the right side of the illustration show the paper feed direction.
- The + sign, the left-pointing arrow, and the red lines shows the direction the image will move on the paper when the value is increased.
- If you select a negative value (for example, -1.0 mm), the image on the paper moves toward the right.

Side Skew


- Use this feature to adjust the paper so that the image for Side 1 and/or Side 2 are not skewed but aligned with each other.



- The factory default setting is zero (0).
- The arrows on the right side of the illustration show the paper feed direction.
- The + sign, the right-curved arrow, and the red lines shows the direction the image will move on the paper when the value is increased.
- If you select a negative value (for example, -1.0 mm), the image on the paper moves toward the left.

FS Direction Image Magnification


- Use this feature to correct for image stretch from Side 1 to Side 2. The image may be enlarged or reduced as necessary.



- **FS** stands for Fast Scan and it enlarges or reduces the image in the direction shown in the illustration above.
- The factory default setting is zero (0).
- The arrows on the right side of the illustration show the paper feed direction.
- The + sign, the up arrow, and the red line shows the direction the image will move on the paper when the value is increased.
- If you select a negative value (for example, -1.0 mm), the image on the paper moves down.

SS Direction Image Magnification

- Use this feature to correct for image stretch from Side 1 to Side 2. The image may be enlarged or reduced as necessary.



- SS** stands for Slow Scan and it enlarges or reduces the image in the direction shown in the illustration above.
 - The factory default setting is zero (0).
 - The arrows on the right side of the illustration show the paper feed direction.
 - The + sign, the left-pointing arrow, and the single, black line shows the direction the image will move on the paper when the value is increased.
 - If you select a negative value (for example, -1.0 mm), the image on the paper moves toward the right.
8. Make the desired adjustments for one the Alignment Profile features (Lead Registration, Side Registration, etc.).

Note

It is recommended that you choose only one Alignment Profile feature until you run another set of Test Prints and evaluate the registration on that output. If you want multiple Alignment Profile features selected, individually select each feature, run Test Prints for that feature, and evaluate the output. After you determine that the output for the selected feature is acceptable, then you can select another Alignment Profile feature to adjust.

Touch the **Close** button on the appropriate screen to save the settings and return to the Alignment Profile window.

Tools Mode.

Alignment Adjustment:
Alignment Profile 1 Close

Lead Registration	Side 1: +2.0 mm Side 2: +2.0 mm	1/1
Side Registration	Side 1: -0.7 mm Side 2: -0.7 mm	
Perpendicularity	Side 1: 0.0 mm Side 2: 0.0 mm	
Side Skew	Side 1: -2.0 mm Side 2: +2.0 mm	
FS Direction Image Magnification	Side 1: 0.000% Side 2: 0.000%	
SS Direction Image Magnification	Side 1: 0.000% Side 2: 0.000%	

Test Print

Run more Test Prints


9. Select **Test Print** to ensure that the output is satisfactory.
 - a. Touch the **2 Sided** button.

Note

If you want to check the registration for 1 Sided prints only, touch the 1 Sided button.

- b. Select **10** test prints by touching the **Up** arrow button to change the number of test prints generated.
 - c. Touch the **Pattern Generator** button.
 - d. Retrieve your output test prints from the digital press.
 - e. Discard the first few prints, as inconsistency tends to be greater with these images.
10. Evaluate the test prints by holding your 2 Sided output at eye level near a light source. This will allow you to see the registration marks for both Side 1 and Side 2 of the output.
 - a. If you determine that the registration between Side 1 and Side 2 is significant and needs adjusting, repeat Steps 7-9 until you achieve satisfactory output. Proceed to the Step 11.
 - b. If the registration between Side 1 and Side 2 is okay, stop now and proceed to the next step.

- Once your output is satisfactory, select **Close** to save these settings and return to the Alignment Adjustment window.



- Select **Close** to save all the settings for this Alignment Profile and return to the *Machine Defaults 2* screen.
- Close out of Tools Mode.

Tip


The Alignment Profile you just created/modified is now in affect for the specific Paper Tray that you selected in the procedure. This Alignment Profile remains in affect until you reenter Tools Mode and deactivate it. To deactivate an Alignment Profile, continue to the next page.

Deactivating an Alignment Adjustment Profile

To switch off or deactivate an Alignment Profile, perform the following steps:

- Reenter **Tools Mode**.
- Select **Alignment Adjustment** from the *Machine Default 2* screen.
- Refer to your Alignment Adjustment Profile Chart where you recorded the selections made for the profile you want to switch off/deactivate.

4. Select the Paper Tray for the profile you want to switch off/deactivate.




The Profile number button selected for this Alignment Profile will be selected. For example, the above illustration shows that Tray 1 is assigned Alignment Profile 1.


5. Touch the **Default** button. This switches off the Alignment Adjustment Profile.
 - Select **Close** to return to the Machine Defaults 2 screen.
6. Exit the Tools Mode by touching the **Close** button.

Finishing System Module Profile (DFA device)

If your digital press has a third-party, Digital Finishing Architecture (DFA) device, connected, enabled, and powered on, the option entitled “**Finishing System Module Profile**” is displayed on the Machine Defaults 2 tab.



Touch the Finishing System Module Profile button to display the Profile List.



To view the settings for a Timing Tab or a Finishing System Profile, touch that button. The settings for a DFA device can only be viewed on the digital press Touch Screen. The settings are enabled on the color server connected to your digital press.

Tip

Some features or options described in this chapter may not display or be selectable depending on the configuration of your machine.


Overview

The Auditron Mode enables you to:

- Change the Tools Mode password
- Establish a separate password for access to the Auditron Mode
- View the number of prints sent through the color server.


Use the following procedure to access the Auditron Administration screens.

1. Press the **Access** button on the Control Panel.
2. Use the Control Panel keypad to enter the Tools Mode five-digit password, and then touch the **Enter** button on the Touch Screen.
3. Touch the **Auditron Administration Pathway** button on the screen. The *Auditron Administration* screen appears.



Initialization


User Accounts are individual accounts that can be set up with print limits, color limits, a password, and copy volume limits. The *Initialization* screen allows you to reset information in User Accounts.



The Initialization screen allows you to:

- Select a total number of User Accounts; the maximum is 300,
- Change the number of User Accounts, or
- Reset all the User Account information and passwords.

Whenever you perform one of the above options, a confirmation screen asks if you are sure you want to initialize the Auditron:



Responding with a “Yes” deletes all the established accounts, and returns the Tools Mode password to the factory default of five ones (11111).

Whether you initially setting up the Auditron, changing the total number of user accounts, or resetting the Auditron, a message appears at the top of the screen when you touch the **Close** button. This message informs you that you must Initialize the Auditron after performing one of the aforementioned functions. Touch the **Initialize Auditron** button and select “Yes” to complete the task.

Create/Modify User Accounts

The Create/Modify User Accounts screen enables you to create user accounts, passwords, or review existing account privileges. You are also able to change the default password for entering the Tools Pathway and to create a new password for the Auditron Mode, if so desired.

Account 1 is reserved for the System Administrator by factory default. This account is set up with access to both Tools and Auditron. The default password is set to 11111 and can be changed by the System Administrator.

Creating a User Account

Use the following procedure to create a User Account.

Note


To undo the last change that you made, touch the **Undo** button at the top of the screen. The last setting that you changed is returned to its previous value.

1. Touch the Create/Modify User Accounts button on the Auditron Administration screen. The Create/Modify User Accounts screen appears.

The screenshot shows the 'Auditron Administration Mode' screen. At the top, a black banner reads 'Auditron Administration Mode. Please input an account number for Account Creation or Change.' Below this is a purple header bar with the text 'Auditron: Create / Modify User Accounts' and three buttons: 'Undo', 'Access Rights', and 'Close'. The main area is titled 'Account Setup' and contains instructions: 'Input the Password using the keypad on the Control Panel. Select Enter after the Password has been entered.' On the left, there is a section for 'Account Number (1-200)' with a dropdown menu showing '1'. Below this are four buttons: 'Next Open Account', 'Next Active Account', 'Previous Account', and 'From Keypad'. On the right, there is a section for 'Input Password' with a button labeled 'Input Password'. Below that is a 'User Password' field containing '11111' and an 'Enter' button. At the bottom left, there is an 'Enter' button.

2. Select the next open account by doing one of the following:
 - a. Touch the From Keypad button.
 - Use the Control Panel keypad to enter the account number for this User Account.
 - Touch the Enter button on the bottom left side of the screen to save your entry; or

- b. Simply touch the Next Open Account button.
3. Set the level of access for the individual using the account by touching the Access Rights button.




4. Touch one of the following buttons:
 - Key Operator Access
 - Auditron Administrator
 - Technical Key Operator Access

Note

The optional Technical Key Operator feature may or may not be activated with your configuration.

5. Touch the Close button to return to the Create/Modify User Accounts screen.



6. Touch the Input Password button.
 - a. Use the Control Panel keypad to enter the unique five-digit password for this account.
 - b. Touch the Enter button in the center of the screen. The password you enter is displayed in the User Password field.
7. Touch the Enter button in the center of the screen to enter your settings into the system.
8. Touch the Close button to return to the Auditron Administration screen.
9. Exit the Auditron Mode to activate the new settings for this User Account.

Modifying a User Account

Use the following procedure to modify a User Account.

Note

To undo the last change that you made, touch the **Undo** button at the top of the screen. The last setting that you changed will be returned to its previous value.

1. Touch the Create/Modify User Accounts button on the Auditron Administration screen. The Create/Modify User Accounts screen appears.
2. Review Steps 2-9 in **Creating a User Account** on for information on how to change specific settings on this screen.
3. Touch the Next Open Account or Previous Account button to modify the settings for additional User Accounts. Touch the Next Active Account button to modify the settings for the next active User Account.
4. Touch the Close button to return to the Auditron Administration screen.
5. Exit the Auditron Mode to activate the new settings for this User Account.

Changing the Tools Mode Password

Use the following procedure to change the Access password for the Tools Mode.

1. Touch the Create/Modify User Accounts button on the Auditron Administration screen. The Create/Modify User Accounts screen appears.

The screenshot shows the 'Auditron Administration Mode' screen. At the top, it says 'Please input an account number for Account Creation or Change.' Below this is a header bar with 'Auditron: Create / Modify User Accounts' and three buttons: 'Undo', 'Access Rights', and 'Close'. The main area is titled 'Account Setup' and contains two columns. The left column has 'Account Number (1-200)' with a field showing '1', and four buttons: 'Next Open Account', 'Next Active Account', 'Previous Account', and 'From Keypad'. The right column has the instruction 'Input the Password using the keypad on the Control Panel. Select Enter after the Password has been entered.' Below this is an 'Input Password' button, a 'User Password' field showing '11111', and an 'Enter' button. At the bottom left is another 'Enter' button.

Account 1 is displayed on the next screen with the default password of five 1s (11111).

2. Touch the Input Password button. Use the Control Panel keypad to enter a new password. The new password is displayed in the User Password field.
3. Touch Enter on the Touch Screen. The new password takes effect the next time you access the Tools Mode.


Creating a Password for the Auditron Mode

Use the following procedure to create a unique password for accessing the Auditron Mode.

1. Touch the **Create/Modify User Accounts** button on the Auditron Administration screen. The **Create/Modify User Accounts** screen appears.
2. Touch the **Next Open Account** button. The number 2 is displayed in the **Account Number** field.

You can use any open account number for the Auditron Pathway password by touching the **Next Active Account** button.

3. Touch the **Input Password** button. Use the Control Panel keypad to enter the unique five-digit password for this account. The password you enter is displayed in the **User Password** field.
4. Touch the **Enter** button to save your entry.
5. Touch the **Access Rights** button at the top of the screen. The *Access Rights* screen appears.



6. Touch the **Auditron Administrator Access** button.
7. Touch the **Close** button.
8. Touch the **Enter** button on the *Create/Modify User Accounts* screen.
9. Touch the **Close** button on the *Create/Modify User Accounts* screen.
10. Exit the Auditron Mode to activate the new password.

Review Printer Job Account

Use the *Review Printer Job Account* screen to determine the number of print jobs sent from the color server connected to your digital press.

The meters show volumes for the following copy types:

Auditron Administration Mode

Auditron:
Review Printer Job Account

Close

Printing Volume

These meters only show the volume of printing jobs from the RIP Server.

You may reset the meters at any time by selecting the Reset button below.

Color Impressions
7888

Black Impressions
1839

Color Large Impressions
822

Reset

Depending on your digital press configuration, you may or may not have an additional printing volume meter on this screen.

To reset these meters to zero, touch the **Reset** button. A confirmation screen asks if you are sure you want to reset the meters.

Note

Resetting these meters does not reset the meters shown on the Meters screen that is accessed through the Machine Details screen on the Touch Screen.

Charts

E Table Settings Chart: Type E1

Paper Type	E Table	Decurler Type	E Table Settings					
			Lower (10 mm)	Lower (6 mm)	Lower (2 mm)	Upper (10 mm)	Upper (6 mm)	Upper (2 mm)
<input type="checkbox"/> Single Paper Weight	<input type="checkbox"/> Type E1	<input type="checkbox"/> Simplex: Straight	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
	<input type="checkbox"/> Type E2	<input type="checkbox"/> Simplex: In Reverse	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm
<input type="checkbox"/> Mixed Paper Weight	<input type="checkbox"/> Type E3	<input type="checkbox"/> Duplex: Side 1 to Side 2						
	<input type="checkbox"/> Type E4	<input type="checkbox"/> Duplex: Side 2 to Side 1						
	<input type="checkbox"/> Type E5	<input type="checkbox"/> Duplex Decurler						
	<input type="checkbox"/> Type E6							

1. Record the original, manufacturer default settings by placing a check mark in the appropriate boxes that apply for the original E Type settings, including Paper Type, E Table, and Decurler Type.
2. Touch the E Table Settings button (from the Decurler E Table Settings window) and then enter the number for each E Type Table Setting in the E Table Settings columns above.

E Table Settings Chart: Type E2

Paper Type	E Table	Decurler Type	E Table Settings					
			Lower (10 mm)	Lower (6 mm)	Lower (2 mm)	Upper (10 mm)	Upper (6 mm)	Upper (2 mm)
<input type="checkbox"/> Single Paper Weight	<input type="checkbox"/> Type E1	<input type="checkbox"/> Simplex: Straight	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
	<input type="checkbox"/> Type E2	<input type="checkbox"/> Simplex: In Reverse	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm
<input type="checkbox"/> Mixed Paper Weight	<input type="checkbox"/> Type E3	<input type="checkbox"/> Duplex: Side 1 to Side 2						
	<input type="checkbox"/> Type E4	<input type="checkbox"/> Duplex: Side 2 to Side 1						
	<input type="checkbox"/> Type E5	<input type="checkbox"/> Duplex Decurler						
	<input type="checkbox"/> Type E6							

1. Record the original, manufacturer default settings by placing a check mark in the appropriate boxes that apply for the original E Type settings, including Paper Type, E Table, and Decurler Type.
2. Touch the E Table Settings button (from the Decurler E Table Settings window) and then enter the number for each E Table Setting in the E Table Settings columns above.

E Table Settings Chart: Type E3

Paper Type	E Table	Decurler Type	E Table Settings					
			Lower (10 mm)	Lower (6 mm)	Lower (2 mm)	Upper (10 mm)	Upper (6 mm)	Upper (2 mm)
<input type="checkbox"/> Single Paper Weight	<input type="checkbox"/> Type E1	<input type="checkbox"/> Simplex: Straight	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
	<input type="checkbox"/> Type E2	<input type="checkbox"/> Simplex: In Reverse	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm
<input type="checkbox"/> Mixed Paper Weight	<input type="checkbox"/> Type E3	<input type="checkbox"/> Duplex: Side 1 to Side 2						
	<input type="checkbox"/> Type E4	<input type="checkbox"/> Duplex: Side 2 to Side 1						
	<input type="checkbox"/> Type E5	<input type="checkbox"/> Duplex Decurler						
	<input type="checkbox"/> Type E6							

1. Record the original, manufacturer default settings by placing a check mark in the appropriate boxes that apply for the original E Type settings, including Paper Type, E Table, and Decurler Type.
2. Touch the E Table Settings button (from the Decurler E Table Settings window) and then enter the number for each E Type Table Setting in the E Table Settings columns above.

E Table Settings Chart: Type E4

Paper Type	E Table	Decurler Type	E Table Settings					
			Lower (10 mm)	Lower (6 mm)	Lower (2 mm)	Upper (10 mm)	Upper (6 mm)	Upper (2 mm)
<input type="checkbox"/> Single Paper Weight	<input type="checkbox"/> Type E1	<input type="checkbox"/> Simplex: Straight	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
	<input type="checkbox"/> Type E2	<input type="checkbox"/> Simplex: In Reverse	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm
<input type="checkbox"/> Mixed Paper Weight	<input type="checkbox"/> Type E3	<input type="checkbox"/> Duplex: Side 1 to Side 2						
	<input type="checkbox"/> Type E4	<input type="checkbox"/> Duplex: Side 2 to Side 1						
	<input type="checkbox"/> Type E5	<input type="checkbox"/> Duplex Decurler						
	<input type="checkbox"/> Type E6							

1. Record the original, manufacturer default settings by placing a check mark in the appropriate boxes that apply for the original E Type settings, including Paper Type, E Table, and Decurler Type.
2. Touch the E Table Settings button (from the Decurler E Table Settings window) and then enter the number for each E Type Table Setting in the E Table Settings columns above.

E Table Settings Chart: Type E5

Paper Type	E Table	Decurler Type	E Table Settings					
			Lower (10 mm)	Lower (6 mm)	Lower (2 mm)	Upper (10 mm)	Upper (6 mm)	Upper (2 mm)
<input type="checkbox"/> Single Paper Weight <input type="checkbox"/> Mixed Paper Weight	<input type="checkbox"/> Type E1	<input type="checkbox"/> Simplex: Straight	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
	<input type="checkbox"/> Type E2	<input type="checkbox"/> Simplex: In Reverse	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm
	<input type="checkbox"/> Type E3	<input type="checkbox"/> Duplex: Side 1 to Side 2						
	<input type="checkbox"/> Type E4	<input type="checkbox"/> Duplex: Side 2 to Side 1						
	<input type="checkbox"/> Type E5	<input type="checkbox"/> Duplex Decurler						
	<input type="checkbox"/> Type E6							

1. Record the original, manufacturer default settings by placing a check mark in the appropriate boxes that apply for the original E Type settings, including Paper Type, E Table, and Decurler Type.
2. Touch the E Table Settings button (from the Decurler E Table Settings window) and then enter the number for each E Type Table Setting in the E Table Settings columns above.

E Table Settings Chart: Type E6

Paper Type	E Table	Decurler Type	E Table Settings					
			Lower (10 mm)	Lower (6 mm)	Lower (2 mm)	Upper (10 mm)	Upper (6 mm)	Upper (2 mm)
<input type="checkbox"/> Single Paper Weight	<input type="checkbox"/> Type E1	<input type="checkbox"/> Simplex: Straight	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
	<input type="checkbox"/> Type E2	<input type="checkbox"/> Simplex: In Reverse	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm	_____ mm
<input type="checkbox"/> Mixed Paper Weight	<input type="checkbox"/> Type E3	<input type="checkbox"/> Duplex: Side 1 to Side 2						
	<input type="checkbox"/> Type E4	<input type="checkbox"/> Duplex: Side 2 to Side 1						
	<input type="checkbox"/> Type E5	<input type="checkbox"/> Duplex Decurler						
	<input type="checkbox"/> Type E6							

1. Record the original, manufacturer default settings by placing a check mark in the appropriate boxes that apply for the original E Type settings, including Paper Type, E Table, and Decurler Type.
2. Touch the E Table Settings button (from the Decurler E Table Settings window) and then enter the number for each E Table Setting in the E Table Settings columns above.

Custom Paper Setup Chart 1

Custom Profile 1							
Paper Tray #	Paper Type Switch	Custom Paper Adjustment					Alignment Adjustment
		Base Range of Paper Type	2nd BTB	Decurler Penetration Amount	Aligner NIP Pressure	Air Assist Operation Selection	Refer to Alignment Profile Number:
<input type="checkbox"/> 1	<input type="checkbox"/> Off <input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated	<input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated	<input type="checkbox"/> Side 1: (50-150 %)	<input type="checkbox"/> Auto <input type="checkbox"/> Type A <input type="checkbox"/> Type B <input type="checkbox"/> Type C <input type="checkbox"/> Type D	<input type="checkbox"/> (-30 to +30) _____ Pulse	<input type="checkbox"/> Auto <input type="checkbox"/> Do Not Operate <input type="checkbox"/> Operate	<input type="checkbox"/> Default <input type="checkbox"/> 1 <input type="checkbox"/> 2 <input type="checkbox"/> 3 <input type="checkbox"/> 4 <input type="checkbox"/> 5 <input type="checkbox"/> 6 <input type="checkbox"/> 7 <input type="checkbox"/> 8 <input type="checkbox"/> 9 <input type="checkbox"/> 10 <input type="checkbox"/> 11 <input type="checkbox"/> 12 <input type="checkbox"/> 13 <input type="checkbox"/> 14 <input type="checkbox"/> 15 <input type="checkbox"/> 16 <input type="checkbox"/> 17 <input type="checkbox"/> 18 <input type="checkbox"/> 19 <input type="checkbox"/> 20
<input type="checkbox"/> 2	<input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	<input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	_____ %	<input type="checkbox"/> Type E1 <input type="checkbox"/> Type E2 <input type="checkbox"/> Type E3 <input type="checkbox"/> Type E4 <input type="checkbox"/> Type E5 <input type="checkbox"/> Type E6			
<input type="checkbox"/> 3	<input type="checkbox"/> Transparency <input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated	<input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated	<input type="checkbox"/> Side 2: (50-150 %)				
<input type="checkbox"/> 4	<input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	<input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	_____ %				

When making selections for your Custom Paper Profile, place a check mark in the appropriate boxes that apply for the settings you select, and where applicable, enter the number you choose for that setting.

Custom Paper Setup Chart 2

Custom Profile 1							
Paper Tray #	Paper Type Switch	Custom Paper Adjustment					Alignment Adjustment
		Base Range of Paper Type	2nd BTB	Decurler Penetration Amount	Aligner NIP Pressure	Air Assist Operation Selection	Refer to Alignment Profile Number:
<input type="checkbox"/> 1	<input type="checkbox"/> Off <input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated <input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	<input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated <input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	<input type="checkbox"/> Side 1: (50-150 %)	<input type="checkbox"/> Auto <input type="checkbox"/> Type A <input type="checkbox"/> Type B <input type="checkbox"/> Type C <input type="checkbox"/> Type D <input type="checkbox"/> Type E1 <input type="checkbox"/> Type E2 <input type="checkbox"/> Type E3 <input type="checkbox"/> Type E4 <input type="checkbox"/> Type E5 <input type="checkbox"/> Type E6	<input type="checkbox"/> (-30 to +30) _____ Pulse	<input type="checkbox"/> Auto <input type="checkbox"/> Do Not Operate <input type="checkbox"/> Operate	<input type="checkbox"/> Default <input type="checkbox"/> 1 <input type="checkbox"/> 2 <input type="checkbox"/> 3 <input type="checkbox"/> 4 <input type="checkbox"/> 5 <input type="checkbox"/> 6 <input type="checkbox"/> 7 <input type="checkbox"/> 8 <input type="checkbox"/> 9 <input type="checkbox"/> 10 <input type="checkbox"/> 11 <input type="checkbox"/> 12 <input type="checkbox"/> 13 <input type="checkbox"/> 14 <input type="checkbox"/> 15 <input type="checkbox"/> 16 <input type="checkbox"/> 17 <input type="checkbox"/> 18 <input type="checkbox"/> 19 <input type="checkbox"/> 20
<input type="checkbox"/> 2	<input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated <input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	<input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated <input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	_____ %				
<input type="checkbox"/> 3	<input type="checkbox"/> Transparency <input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated <input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	<input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated <input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	<input type="checkbox"/> Side 2: (50-150 %)				
<input type="checkbox"/> 4	<input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated <input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	<input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated <input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	_____ %				

When making selections for your Custom Paper Profile, place a check mark in the appropriate boxes that apply for the settings you select, and where applicable, enter the number you choose for that setting.

Custom Paper Setup Chart 3

Custom Profile 1							
Paper Tray #	Paper Type Switch	Custom Paper Adjustment					Alignment Adjustment
		Base Range of Paper Type	2nd BTB	Decurler Penetration Amount	Aligner NIP Pressure	Air Assist Operation Selection	Refer to Alignment Profile Number:
<input type="checkbox"/> 1	<input type="checkbox"/> Off <input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated	<input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated	<input type="checkbox"/> Side 1: (50-150 %)	<input type="checkbox"/> Auto <input type="checkbox"/> Type A <input type="checkbox"/> Type B <input type="checkbox"/> Type C <input type="checkbox"/> Type D	<input type="checkbox"/> (-30 to +30) _____ Pulse	<input type="checkbox"/> Auto <input type="checkbox"/> Do Not Operate <input type="checkbox"/> Operate	<input type="checkbox"/> Default <input type="checkbox"/> 1 <input type="checkbox"/> 2 <input type="checkbox"/> 3 <input type="checkbox"/> 4 <input type="checkbox"/> 5 <input type="checkbox"/> 6 <input type="checkbox"/> 7 <input type="checkbox"/> 8 <input type="checkbox"/> 9 <input type="checkbox"/> 10 <input type="checkbox"/> 11 <input type="checkbox"/> 12 <input type="checkbox"/> 13 <input type="checkbox"/> 14 <input type="checkbox"/> 15 <input type="checkbox"/> 16 <input type="checkbox"/> 17 <input type="checkbox"/> 18 <input type="checkbox"/> 19 <input type="checkbox"/> 20
<input type="checkbox"/> 2	<input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	<input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	_____ %	<input type="checkbox"/> Type E1 <input type="checkbox"/> Type E2 <input type="checkbox"/> Type E3 <input type="checkbox"/> Type E4 <input type="checkbox"/> Type E5 <input type="checkbox"/> Type E6			
<input type="checkbox"/> 3	<input type="checkbox"/> Transparency <input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated	<input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated	<input type="checkbox"/> Side 2: (50-150 %)				
<input type="checkbox"/> 4	<input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	<input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	_____ %				

When making selections for your Custom Paper Profile, enter the Customer Profile number. Place a check mark in the appropriate boxes that apply for the settings you select, and where applicable, enter the number you choose for those settings.

Custom Paper Setup Chart 4

Custom Profile 1							
Paper Tray #	Paper Type Switch	Custom Paper Adjustment					Alignment Adjustment
		Base Range of Paper Type	2nd BTB	Decurler Penetration Amount	Aligner NIP Pressure	Air Assist Operation Selection	Refer to Alignment Profile Number:
<input type="checkbox"/> 1	<input type="checkbox"/> Off <input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated	<input type="checkbox"/> 60-80 g/m ² Uncoated <input type="checkbox"/> 81-105 g/m ² Uncoated <input type="checkbox"/> 106-135 g/m ² Uncoated	<input type="checkbox"/> Side 1: (50-150 %)	<input type="checkbox"/> Auto <input type="checkbox"/> Type A <input type="checkbox"/> Type B <input type="checkbox"/> Type C <input type="checkbox"/> Type D	<input type="checkbox"/> (-30 to +30) _____ Pulse	<input type="checkbox"/> Auto <input type="checkbox"/> Do Not Operate <input type="checkbox"/> Operate	<input type="checkbox"/> Default <input type="checkbox"/> 1 <input type="checkbox"/> 2 <input type="checkbox"/> 3 <input type="checkbox"/> 4 <input type="checkbox"/> 5 <input type="checkbox"/> 6 <input type="checkbox"/> 7 <input type="checkbox"/> 8 <input type="checkbox"/> 9 <input type="checkbox"/> 10 <input type="checkbox"/> 11 <input type="checkbox"/> 12 <input type="checkbox"/> 13 <input type="checkbox"/> 14 <input type="checkbox"/> 15 <input type="checkbox"/> 16 <input type="checkbox"/> 17 <input type="checkbox"/> 18 <input type="checkbox"/> 19 <input type="checkbox"/> 20
<input type="checkbox"/> 2	<input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	<input type="checkbox"/> 136-186 g/m ² Uncoated <input type="checkbox"/> 187-220 g/m ² Uncoated <input type="checkbox"/> 221-300 g/m ² Uncoated	_____ %	<input type="checkbox"/> Type E1 <input type="checkbox"/> Type E2 <input type="checkbox"/> Type E3 <input type="checkbox"/> Type E4 <input type="checkbox"/> Type E5 <input type="checkbox"/> Type E6			
<input type="checkbox"/> 3	<input type="checkbox"/> Transparency <input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated	<input type="checkbox"/> 60-80 g/m ² Coated <input type="checkbox"/> 81-105 g/m ² Coated	<input type="checkbox"/> Side 2: (50-150 %)				
<input type="checkbox"/> 4	<input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	<input type="checkbox"/> 106-135 g/m ² Coated <input type="checkbox"/> 136-186 g/m ² Coated <input type="checkbox"/> 187-220 g/m ² Coated <input type="checkbox"/> 221-300 g/m ² Coated	_____ %				

When making selections for your Custom Paper Profile, enter the Customer Profile number. Place a check mark in the appropriate boxes that apply for the settings you select, and where applicable, enter the number you choose for those settings.

Alignment Adjustment Profile Chart 1

Alignment Profile 1					
<input type="checkbox"/> Lead Registration	<input type="checkbox"/> Side Registration	<input type="checkbox"/> Perpendicularity	<input type="checkbox"/> Side Skew	<input type="checkbox"/> FS Direction Image Magnification	<input type="checkbox"/> SS Direction Image Magnification
<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____mm	<input type="checkbox"/> Side 1: (-1.2 to +1.2) _____mm	<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 1: (-0.400 to +0.400) _____%	<input type="checkbox"/> Side 1: (-0.400 to +0.400) _____%
<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____mm	<input type="checkbox"/> Side 2: (-1.2 to +1.2) _____mm	<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 2: (-0.400 to +0.400) _____%	<input type="checkbox"/> Side 2: (-0.400 to +0.400) _____%

When making selections for your Alignment Adjustment Profile, place a check mark in the appropriate boxes that apply for the settings you select, and where applicable, enter the number you choose for the selected settings.

Alignment Adjustment Profile Chart 2

Alignment Profile 1					
<input type="checkbox"/> Lead Registration	<input type="checkbox"/> Side Registration	<input type="checkbox"/> Perpendicularity	<input type="checkbox"/> Side Skew	<input type="checkbox"/> FS Direction Image Magnification	<input type="checkbox"/> SS Direction Image Magnification
<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____mm	<input type="checkbox"/> Side 1: (-1.2 to +1.2) _____mm	<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 1: (-0.400 to +0.400) _____%	<input type="checkbox"/> Side 1: (-0.400 to +0.400) _____%
<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____mm	<input type="checkbox"/> Side 2: (-1.2 to +1.2) _____mm	<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 2: (-0.400 to +0.400) _____%	<input type="checkbox"/> Side 2: (-0.400 to +0.400) _____%

When making selections for your Alignment Adjustment Profile, place a check mark in the appropriate boxes that apply for the settings you select, and where applicable, enter the number you choose for the selected settings.

Alignment Adjustment Profile Chart 3

Alignment Profile 1					
<input type="checkbox"/> Lead Registration	<input type="checkbox"/> Side Registration	<input type="checkbox"/> Perpendicularity	<input type="checkbox"/> Side Skew	<input type="checkbox"/> FS Direction Image Magnification	<input type="checkbox"/> SS Direction Image Magnification
<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____mm	<input type="checkbox"/> Side 1: (-1.2 to +1.2) _____mm	<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 1: (-0.400 to +0.400) _____%	<input type="checkbox"/> Side 1: (-0.400 to +0.400) _____%
<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____mm	<input type="checkbox"/> Side 2: (-1.2 to +1.2) _____mm	<input type="checkbox"/> Side 2: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 2: (-0.400 to +0.400) _____%	<input type="checkbox"/> Side 2: (-0.400 to +0.400) _____%

When making selections for your Alignment Adjustment Profile, enter the Alignment Profile Number. Place a check mark in the appropriate boxes that apply for the settings you select, and where applicable, enter the number you choose for the selected settings.

Alignment Adjustment Profile Chart 4

Alignment Profile 1					
<input type="checkbox"/> Lead Registration	<input type="checkbox"/> Side Registration	<input type="checkbox"/> Perpendicularity	<input type="checkbox"/> Side Skew	<input type="checkbox"/> FS Direction Image Magnification	<input type="checkbox"/> SS Direction Image Magnification
<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____mm <input type="checkbox"/> Side 2: (-2.0 to +2.0) _____mm	<input type="checkbox"/> Side 1: (-1.2 to +1.2) _____mm <input type="checkbox"/> Side 2: (-1.2 to +1.2) _____mm	<input type="checkbox"/> Side 1: (-2.0 to +2.0) _____ mm <input type="checkbox"/> Side 2: (-2.0 to +2.0) _____ mm	<input type="checkbox"/> Side 1: (-0.400 to +0.400) _____% <input type="checkbox"/> Side 2: (-0.400 to +0.400) _____%	<input type="checkbox"/> Side 1: (-0.400 to +0.400) _____% <input type="checkbox"/> Side 2: (-0.400 to +0.400) _____%

When making selections for your Alignment Adjustment Profile, enter the Alignment Profile Number. Place a check mark in the appropriate boxes that apply for the settings you select, and where applicable, enter the number you choose for the selected settings.

