

Patch Installation Instructions

L3 Support Team

Product(s):	Xerox EX-i 180 Print Server Powered by Fiery	Date:	July 2020
Title:	FIT102104248.ps Installation Instructions	Page:	1 of 2

Purpose

This Fiery EX-i 180 software patch is being provided to enable the Fiery print server to use the optional Xerox Adaptive CMYK Plus features.

- For Color managed Preview, please use latest Command WorkStation 6.4 from EFI download center.

Only customers who have the Xerox Adaptive CMYK Plus kit should install this patch.

Installation Instructions

Note: The customer or a member of the Xerox Service Team may install this software.

Note: This patch is exclusive, it must be installed by itself, and the server must be rebooted or restarted once. After that, other patches may be installed on the server.

Kit Contents

Qty.	Description
1	Patch Installation Instructions
1	Customer User Addendum
1	FIT102104248.ps patch
1	uninstall_linux_v1.ps

1. The Fiery controller must be at **Idle**.
2. Import the file FIT102104248.ps using Command WorkStation to the Direct connection.
3. Wait until the file finishes processing and Command WorkStation or the LCD show Idle.
4. From Command WorkStation choose Server/Reboot Server, or from the Fiery LCD select Shut down/Reboot System.
5. Wait until the Fiery controller reaches Idle and print out the Configuration page.
6. Verify the **System Update Info** section of the Configuration page. It should contain the patch number FIT102104248.

Prerequisites

- Previous working knowledge of the Fiery EX-i 180 system.
- The Fiery EX-i 180 software must have **version 1.2** installed prior to installing this patch.
- The following prerequisite (s) must be installed before installing this patch. Prerequisite patches are obtained via EFI Auto Updates, System Updates, or by contacting our Xerox L2 Support teams.

- FIT102088107

Uninstall Instructions

Note: The Uninstall patch will only uninstall FIT102104248.

Important Information for FIT102104248

- Image viewer shows separation name as Cyan, Magenta, Yellow, and Black while Vivid_kit/Fluo_Kit workflow is in use.
- If you observe overlapping objects in output when processing few files with Vivid_kit preset, please enable 'Composite overprint' from Job Properties/Color tab/Color Settings.
- Printing of files with CMYK Plus colors is supported only through Command WorkStation and not through Fiery drivers.

1. Make sure the Fiery is Idle.
2. Import the uninstall_linux_v1.ps file using Command WorkStation.
3. Wait until the file finishes processing and Command WorkStation or the LCD show Idle. User should wait one minute for complete installation of patch.
4. From Command WorkStation, choose Server / Reboot Server, or from the Fiery LCD, select Shut down / Reboot System.

	Date: July 2020	Page: 2 of 2
--	--------------------	-----------------

- ___ 5. Wait until the Fiery comes to Idle and print the Configuration page.
- ___ 6. Verify that FIT102104248 is no longer on the Configuration page.